



VHF MARINE TRANSCEIVER

IC-M35



"Automatic Volume Adjustment"

"Noise Cancelling Mic"

"Loud, Instant Maximum Audio"

CLEAR VOICE BOOST

(Clear Voice + Voice Boost)

In marine environments there are many sources of noise that can affect the quality of your communication, such as engine noise, roar of waves and more. The IC-M35 constantly transmits clear voice and provides boosted audio even in those circumstances and ensures your conversation is sent and received as clearly as possible no matter how noisy the background is!

And yes, it floats too!

Continuing the legacy from the IC-M33, the IC-M35 floats for you to be able to retrieve it if you should ever lose it overboard. The IC-M35 floats even when the optional speaker microphone, HM-165 is attached.



BUOYANT

Waterproof
1m depth for 30 minutes

Rugged
MIL-STD 810



LOUD button

When you need an instant "boost" in the volume, a simple push of the "LOUD" button gives you full volume immediately. In addition, holding the "LOUD" button mutes the audio output.

Noise cancelling microphone

The sub-microphone on the rear panel inverts phase and cancels out ambient noise from the main microphone. As a result, the IC-M35 reduces the affect of background noise (particularly treble noise) from the transmitted signal and makes it easier to catch voice communication.

Automatic volume adjustment

When in an engine room or high noise environment, the sub-microphone detects the ambient noise and the IC-M35 automatically increases the volume output to suit the surrounding environment.

Low power consumption

Although the IC-M35 delivers a high 6W*1 RF output and 700mW audio output, its current saving circuit offers a practical 8 hours*2 of operating time with the supplied 980mAh Lithium-Ion battery pack.

*1 Depending on version.

*2 Typical operation with Tx (Hi): Rx: standby=5:5:90

Large buttons and slim dimensions

Thanks to the large, easy-to-operate buttons, the IC-M35 provides intuitive operation. A pinched-waist slender body makes it easy to hold and carry the radio, and is surprisingly compact for a floating radio.

Other features

- Waterproof construction equivalent to IPX7 (1m depth for 30 minutes)
- Dual/Tri-watch functions
- 4-step battery life indicator
- Auto scan function
- Instant access to Ch 16 or programmable call channel

• Audio output power (at 10% distortion) :

Internal speaker 700mW typical (with a 16Ω load)
External speaker 200mW (with an 8Ω load)

Applicable U.S. Military Specifications & IP Rating

Standard	Method	MIL 810 F	Procedure
Low Pressure	509.4		I, II
High Temperature	501.4		I, II
Low Temperature	502.4		I, II
Solar Radiation	505.4		I
Rain	506.4		I, III
Humidity	507.4		—
Salt fog	509.4		—
Dust	510.4		I
Immersion	512.4		I
Vibration	514.5		I
Shock	516.5		I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard

Dust & Water IP57 (Dust-protection and waterproof protection)

Supplied accessories

- Battery pack, BP-252
- Battery charger, BC-173
- Belt clip, MB-109
- AC adapter, BC-147*
- Antenna, FA-SC58V
- Hand strap
- Battery case, BP-251 (UK version only)

(* Not supplied depending on version.)

SPECIFICATIONS**GENERAL**

- Frequency range Tx : 156.000–161.450MHz
Rx : 156.000–163.425MHz
- Usable channels : INT, USA* channels;
70 programmable channels
(* Depending on version)
- Type of emission : 16K0G3E (FM)
- Current drain (at 7.4V DC) :
Tx 6W output 1.5A typical
5W output 1.3A typical
Rx AF max.
Internal speaker 300mA typical
External speaker 200mA typical
Power save 10mA typical
- Operating temperature range : –15°C to +55°C
- Antenna impedance : 50Ω (STUD)
- Dimensions (W×H×D) : 62×139.5×43 mm
(projections not included)
- Weight (approx.) : 295g (with BP-252, MB-109 and antenna)

TRANSMITTER

- Output power (Hi/Low) : 6/1W*
2/1W (with alkaline battery)
* Australia version 5/1W
* German version 1/0.5W
- Max. frequency deviation : ± 5.0kHz
- Frequency error : ± 1.5kHz
- Spurious emissions : 0.25μW
- Adjacent channel power : 70dB
- Audio harmonic distortion : Less than 10% (at 60% dev.)
- Residual modulation : 40dB


RECEIVER

- Sensitivity (20dB SINAD) : –2dBμ emf typical
- Squelch sensitivity : –6dBμ emf typical (threshold)
- Adjacent Ch. selectivity : 70dB
- Spurious response : 70dB*
* Australia version 65dB
- Intermodulation rejection : 68dB
- Hum and noise ratio : 40dB

Measurements made in accordance with EN301-178-2. All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



BP-251 BATTERY CASE
Battery case for LR03 (AAA)×5 alkaline cells.
Output power: 2W.
BP-252 Li-Ion BATTERY PACK 7.4V, 950 mAh (min.) 980mAh (typ.). Provides 8 hours operating time (approx.).
(Typical operation with Tx (Hi): Rx: standby=5:5:90)



BC-173 DESKTOP CHARGER
+ **BC-147*1 AC ADAPTER**
Charges the battery pack, BP-252, in 10 hours (approx.).

*1 BC-147SA for 120V AC. BC-147SE for 230V AC. BC-147SV for 240V AC.

*2 BC-123SA for 120V AC. BC-145SE for 230V AC. BC-145SV for 240V AC. BC-145SUK for 230V UK plug.



BC-162 DESKTOP CHARGER
+ **BC-145/BC-123*2 AC ADAPTER**
Rapidly charges the battery pack, BP-252, in 2 hours (approx.).



HM-165 SPEAKER-MICROPHONE
Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).



MB-109 BELT CLIP
Alligator type.
Same as supplied.



FA-SC58V ANTENNA
Soft flexible antenna.
Same as supplied.

Please note : The noise cancellation can produce little or no effect in some conditions depending on type of noise, or the position and distance between the noise source and the microphone, etc.
The noise cancellation does not work when an optional external speaker-microphone is connected.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries.

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!**Icom America Inc.**

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : <http://www.icomcanada.com>

Icom Brazil

Rua Itooró, 444 Padre Eustáquio
Belo Horizonte MG,
CEP: 30130-150, Brazil
Phone : +55 (31) 3582 8847
Fax : +55 (31) 3582 8987
E-mail : sales@icombrasil.com

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone : +49 (6196) 76685-0
Fax : +49 (6196) 76685-50
E-mail : info@icom-europe.com
URL : <http://www.icom-europe.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

Icom Polska Sp. Z o.o.

90-286 Gdansk, Jaskowa Dolina St. 75, Poland
Phone : +48 (58) 551 0484
Fax : +48 (58) 551 4720
E-mail : icompolksa@icompolksa.com.pl
URL : <http://www.icompolksa.com.pl>

Icom (UK) Ltd.

Blacksole House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone : +44 (0) 1227 741741
Fax : +44 (0) 1227 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Bréjondej des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

hamTECH
Naše kontaktné údaje:

SOUND DESIGN s.r.o.
Pribešova 19/A
841 05 Bratislava

Telefón: +421 2 65 45 65 45

Mobil +421 918 246 789

E-mail: hamtech@hamtech.sk

Web: www.hamtech.sk